# ZOTAC

## SKU: ZP-QK5P1000



# ΖΟΤΔΟ





## **TECHNICAL SPECIFICATIONS**

- FEATURES Intel Core i5-7300U processor Quad HDMI 2.0 output powered by NVIDIA Quadro P1000 graphics Support software EDID emulation for digital signage application Hardware watchdog timer Rugged full metal active-cooling enclosure

- GRAPHICS ENGINE NVIDIA Quadro P1000 for Embedded GPU w/128-bit 4GB GDDR5 NVIDIA Pascal architecture 640 NVIDIA CUDA cores Support NVIDIA Vulkan 1.1, Microsoft DirectX 12, OpenGL 4.5 HDMI 2.0: 4096 x 2160@60Hz

DUAL GIGABIT LAN

802.11 AC WIFI

MEMORY • 2 x DDR4-2133 SO-DIMM slot (Up to 32GB)

ULTRA HD

QK5P1000

## DISPLAY OUTPUT

- AUDIO INTERFACE 8-channel digital audio output via HDMI port S/PDIF optical audio output 3.5mm stereo headphone jack 3.5mm microphone jack

WATCHDOG TIMER

## • DC 19V, 120W

# PHYSICAL DIMENSIONS • Length: 210.0mm (8.27in) • Width: 176.6mm (6.95in) • Height: 44.4mm (1.75in)

## SUPPORTED OS • Microsoft Windows • Ubuntu 16.04 LTS

- INSIDE THE BOX ZBOX PRO QK5P1000 Universal AC adapter Power Cord (bundled cable type dependent on region) L-mount kit 2 x Wi-Fi antenna USB flash with software & user's manual



©2019 ZOTAC Technology Ltd. All rights reserved. All company and/or product names may be trade names, trademarks and/or registered trademarks of the respective owners with which they are associated. ZOTAC Technology Ltd. does not warrant the accuracy, completeness or reliability of information, materials and other items contained on this print, image, website, or server. No liability is assumed with respect to the use of the information contained herein.

RS-232

1

SDXC CARD READER

USB 3.0 SUPERSPEED



